



KRAMER

WP-501

Active Wall Plate Solution for Simple Room
Control & Signal Switching

| VGA/UXGA - 15-pin HD | Microphone -
3.5/6.5mm | Ethernet - RJ-45



The WP-501 is a switcher for computer graphics video, composite video, stereo audio and microphone signals. It routes one of three AV input sources (one front & two rear) to a display and controls the display by IR or RS-232 commands. With some of its input connectors on the back panel, it perfectly fits rooms with permanently installed PCs and video sources

FEATURES

Front Panel Connections - Inputs: 1 computer graphics video on a 15-pin HD connector, unbalanced stereo & 1 microphone on 3.5mm mini jacks

Rear Panel Connections - Inputs: 1 computer graphics video with unbalanced stereo, 1 composite video and stereo audio on terminal blocks; Outputs: 1 composite video, 1 computer graphics video and 2 audio outputs on terminal blocks; 2 relays & 1 IR on terminal blocks; 1 Ethernet on an RJ-45 connection

Controls - 2 volume control knobs: 1 audio and 1 microphone; front panel buttons: 1 projector power and 3 input selection. Each programmable button performs command macros such as changing projector inputs; 2 low voltage relays

Display Control Ports - IR and bidirectional RS-232 for controlling the display device

EDID Storage - EDID information can be stored and modified from a PC using EDID Designer software

Kramer Site-CTRL™ Compatible - For network remote control and management using Kramer Site-CTRL software over the Ethernet port

Mud Ring Supplied for Easy Installation

Dimensions - 16.2cm x 3.36cm x 11.4cm (6.38" x 1.32" x 4.49") US W, D, H

Colors - Available in white, black, gray and brushed aluminum



KRAMER

TECHNICAL SPECIFICATIONS

INPUTS:	1 composite video, 1Vpp/75 Ω on an RCA connector; 2 VGA (PC) on 15-pin HD connectors; 2 unbalanced stereo audio on 3.5mm mini jacks; 1 unbalanced stereo audio on 2 RCA connectors; 1 condenser/dynamic microphone on a 3.5mm mini jack
OUTPUTS:	1 video out 2-pin terminal block connector, 2 audio out 3-pin terminal block connector unbalanced stereo audio, 1 VGA (PC) out 10-pin terminal block connector
PORTS:	Ethernet, 1 IR out on terminal block connectors, 1 RS-232 on terminal block connectors, 1 USB connector
SUPPORTED RS-232 BAUD RATES:	Up to 115200
SUPPORTED RESOLUTIONS:	640x480px60Hz (IBM VGA), 640x480px67Hz (Apple Mac II), 640x480px72Hz (VESA), 640x480px75Hz (VESA), 800x600px56Hz (VESA), 800x 600px60Hz (VESA), 800x600px72Hz (VESA), 800x600px75Hz (VESA), 1024x768px60Hz (VESA), 1024x768px70Hz (VESA), 1024x768px75Hz (VESA), 1280x1024px75Hz (VESA), 1280x1024px60Hz (VESA STD), 1280x960px60Hz (VESA STD), 1400x1050px60Hz (VESA STD), 1440x900px60Hz (VESA STD), 1600x1200px60Hz (VESA STD)
POWER CONSUMPTION:	12V, 5A
INCLUDED ACCESSORIES:	Power supply, screwdriver, mud ring
OPTIONS:	USB cable 0.91m (3ft), WP-500 installation cable
Product Dimension	US: 16.20cm x 0.00cm x 11.43cm (6.38" x 0.00" x 4.50") W, D, H
Product Weight	US: 0.3kg (0.6lbs) approx
Shipping Dimension	US: 35.10cm x 21.20cm x 7.20cm (13.82" x 8.35" x 2.83") W, D, H
Shipping Weight	US: 0.8kg (1.7lbs) approx

