

**VANZEL**

# **USER MANUAL**

---

Model : SH-SP208


**4K HDMI Switch/Splitter 2x8**

**Enjoy the vivid world!**

# INTRODUCTION

## 4K HDMI Switcher/Splitter 2x8

This HDMI Switcher/Splitter 2x8 can connect 2 HD signal sources with 8 HD display terminals. It can easily split 2-way HD signal sources to 8 HDTVs or projectors which support HD. It also can amplify the HDMI signal. The two input HD signal sources can be switched freely. The HDMI Switch/Splitter 2x8 can support highest video resolution 3840x2160/30Hz.



## Features:

- Support 3D
- Support highest video resolution 3840x2160/30Hz
- Support 3 Gbps data rate for tmds clock up to 300Mhz
- Support 8/10/12 bit deep color
- Support standard AWG26 cable: When the resolution is 1080p and below, input up to 10 metres , output up to 15 metres; When the resolution is 4K, input up to 5 metres , output up to 10 metres
- Support single high definition display and multiple output HD signal sources, such as DVD Players ,A/V Receivers and set-top box.
- Need DC 5V/1A power supply
- HDCP v1.4 compliant

## Specifications:

HDMI resolution .....	4K/1080p/1080i/720p/576p/576i/480p/480i
Support video format .....	.8/10/12bit deep color
Support audio format .....	.LPCM
Max bandwidth .....	300MHz
Max baud rate .....	3Gbps
Input cable distance .....	(1080p resolution) ≤10m,(4K resolution)≤5m AWG26 HDMI standard cable
Output cable distance .....	(1080p resolution) ≤15m,(4K resolution)≤10m AWG26 HDMI standard cable
HDMI input port .....	2
HDMI output port .....	8
Max working current .....	0.7 A
Power adapter format: .....	Input:AC (50HZ, 60HZ) 100V-240V; Output: DC5V/1A
Operating Temperature range .....	(-15 to +55 C)
Operating Humidity range .....	5 to 90%RH (No Condensation)
Dimension (L x W x H) .....	278x136x24 (mm)
Weight .....	640g

## The remote control:




- 1) Press the button 1 to switch to the input 1, L1 indicator lights up
- 2) Press the button 2 to switch to the input 2, L2 indicator lights up

## Pictures of Product:



## Physical interface diagram



## Operation and connections:

1. Connect 2 HD signal sources to the inputs of HDMI Switch/Splitter 2x8
2. Connect 8 HD display devices to the outputs of HDMI Switch/Splitter 2x8
3. Connect 5V/1A power adapter with HDMI Switch/Splitter 2x8
4. Button operation: Reset button is used for system reset; Select button is used for switching the input sources

## The Package includes:

1. HDMI Switch/Splitter 2x8	1pc
2. IR Remote Control	1pc
3. 5V DC Power adapter	1pc
4. User Manual	1pc