



## 3232S-XL

32x32 Analog Balanced Stereo Audio Matrix  
Switcher

| Ethernet - RJ-45



The Lassen XL Series offers flexibility and adaptability to any application where saving space and costs are important. 3232S-XL is a 32x32 analog balanced stereo audio matrix switcher, available in a compact 3RU frame. It offers control via the front panel or remotely via RS-232 or Ethernet

### TECHNICAL SPECIFICATIONS

Inputs	32 Balanced/Unbalanced Stereo Analog Audio: On 5-pin terminal block connectors
Outputs	32 Balanced/Unbalanced Stereo Analog Audio: On 5-pin terminal block connectors
Ports	2 Sync: On BNC connectors
	1 Ethernet: On an RJ-45 connector
	1 RS-232/422: On a 9-pin D-sub connector
	2 RS-485: On male mini-XLR connectors, for control panel
	1 AC Power: On an AC power connector
Analog Audio	Input - Max. Source Level +24dBu
	Input - Impedance >20k $\Omega$
	Output - Max. Source Level +24dBu balanced +18dBu unbalanced
	Output - Impedance <50 $\Omega$
Enclosure	Size: 19" — 3U — mounts in a standard 19" rack
	Dimensions: 19" x 18.5" x 5.25" W, D, H