


Key Features

- Supports Auto-Tracking and Audio Transmission
- Working with NEXIS Media Station, PM212 Can Become a Microphone to Record the Presenter's Voice
- Easy Control of Start/Stop Tracking and Mute Functions by Built-in Buttons
- Built-in Rechargeable Lithium Battery

Product Interface



- Ø3.5 audio input jack
- 2 Power / tracking on-off
- 3 Microphone pairing / mute
- 4 Power input USB Micro-B port

Specification

PM212	
Tracking and Indicators	
Effective Distance (tracking and audio)	2~12m radius
Upper Indicators	Power on-off / tracking start-pause
Lower Indicators	Wireless pairing / mute
Audio	
Audio Input	Ф3.5mm phone jack
	Built-in Microphone
General	
Power Supply	Built-in rechargeable lithium battery, 3.7V, 800mA Interface: USB Micro-B
Temperature	0~50°C
Battery Life	4hrs, after fully charged
Dimension	83(L) x 41.5(W) x 18.15(H)mm
Weight	67g