

Full HD Standard Signage SM5J

LG webOS Standard Signage



webOS Smart Platform



Built-in Speaker



Support Landscape / Portrait Mode



Compatibility with Promota*

SM5J

Size	32	
Operation Time	24 hrs / 7 days	
Brightness	400 nit	
Screen Resolution	1,920 x 1,080	
LG's Solution Compatibility	Promota App*, LG ConnectedCare	
Speaker	Built-in	
Interface	HDMI(3) /USB 2.0/ RS232C/ RJ45/ IR / Audio	
Built-in Speaker	10W + 10W	
Operation Hours (Hours / Day)	24/7	
Orientation	Portrait / Landscape	



HIGH-PERFORMANCE WITH WEBOS 6.0

webOS 6.0, upgraded in SoC and web engine, is available on SM5J for a smooth execution of several tasks. LG webOS smart signage platform enhances user convenience with intuitive GUI and provides to SI or/and developers simple app development tools such as SDK (Software Development Kit), SCAP, sample applications.



MOBILE & WEB MONITORING

Through the Control Manager, the embedded web monitoring solution, you can control and monitor the status of the SM5J series displays in different locations in real-time. It is available on internet connected devices, allowing you to flexibly and rapidly respond to emergency situations.

- * The mobile devices need be connected with the Signage IP address and can control one Signage at a time.
- ** Control Manager is optimized for Google Chrome 56 version and above.



VARIOUS SENSOR CONNECTION

LG webOS smart signage platform helps to easily provide additional solutions by supporting simple connections with external sensors* such as GPIO, NFC/RFID, temperature sensors, etc., via USB plug-in.

* External sensors need to be purchased separately and tested for compatibility with webOS platform.



COMPATIBLE WITH AV CONTROL SYSTEM

The SM5J series supports Crestron Connected® for high compatibility with professional AV controls to achieve seamless integration and automated control*, boosting business management efficiency.

* Network based control



REAL-TIME LG ConnectedCare SERVICE

Maintenance is easy and fast with the optional LG ConnectedCare* service, a cloud service solution provided by LG. It remotely manages the status of displays in client workplaces for fault diagnosis and remote-control services, supporting the stable operation of clients' businesses.

* The availability of the 'LG ConnectedCare' service differs by region, and it needs to be purchased separately.



LG'S SIMPLE ADVERTISEMENT HELPER, PROMOTA

Using LG's Promota* application, downloadable on a mobile device, you can easily create your own display contents. With Promota, you can add text and images to create an online profile for your business as well as deliver information such as event news, seasonal menus, promotions, and even more while recommending easy-to-use templates relevant to your industry.

* Promota can be downloaded from the App Store and Google Play store.



With Beacon and Bluetooth® Low Energy (BLE), shop managers can provide coupons and information in real-time.

CONNECTIVITY

Content Mirroring among devices is available on a Wi-Fi network.

WIRELESS ACCESS POINT The SM5J series operates as a virtual router which can be an wireless access point for mobile devices.



* Jack Panels may differ from the above image, so please contact LG sales team to verify before ordering.

Specification

		Model Name	SM5J
		Screen Size	32
		Panel Technology	IPS
		Back Light Type	Direct
		Aspect Ratio	16:9
		Native Resolution	1920 x 1080 (FHD)
		Refresh Rate	60Hz
Panel		Brightness	400nit (Typ.)
		Contrast Ratio	1,100:1
		Viewing Angle (H x V)	178 x 178
		Color Depth	10-bit (D), 1.07Bilion colors
		Response Time	10ms (G to G)
			1%
		Surface Treatment (Haze)	
		Operation Hours (Hours / Day)	24/7
		Portrait / Landscape	Yes / Yes
		Input	HDMI (3, HDCP 2.2), USB 2.0 (Type A)
Connectivity	Output	Output	Audio Out (Off / Fixed / Variable)
		External Control	RS-232C In / Out (Phone-jack Type), RJ45 In (LAN), IR In (Phone-jack Type)
		Bezel Color	Black
		Bezel Width	13mm (T/ R / L), 18mm (B)
		Weight (Head)	5.7Kg
		Weight (Head+Stand)	6.5Kg
Mechanical Speci	fication	Packed Weight	7.4Кg
		Monitor Dimension (W x H x D)	729.4mm x 428.9mm x 55.5mm
		Monitor Dimensions with Stand (W x H x D)	729.4mm x 481mm x 154.2mm
		Carton Dimensions (W x H x D) (Box outer size)	810mm x 510mm x 132mm
		VESATM Standard Mount Interface	200 x 200
		Key Feature	Internal Memory 8 GB, Built-in Wi-Fi, Temperature Sensor, Auto Brightness Sensor, Local Key Operation, webOS 6.0, Embedded CMS (Local Contents Scheduling, Group Manager), USB Plug & Play, Fail Over, Background Image (Booting Logo Image, No Signal Image), Screen Share, Play via URL, Setting Data Cloning, SNMP, ISM (Image Sticking Minimization) Method, Control Manager, Smart Energy Saving, PM Mode, Wake on LAN, Beacon, HDMI-CEC (Compatibility may differ by equipment), SI Sever Setting, webRTC, Pro:Idiom
		Operation Temperature	0 °C to 40 °C
Environment Cor	nditions	Operation Humidity	10 % to 80 %
		Power Supply	AC 100-240V~, 50/60Hz
Power		Power Type	Built-In Power
		Тур.	55W
		Max.	75W
		BTU (British Thermal Unit)	187.67BTU / Hr (Typ.), 255.911BTU / Hr (Max.)
Power Consumption		Smart Enegy Saving	38.5W
		DPM	0.5W
		Power off	0.5W
Sound		Speaker	10W x 2EA
		Safety	CB / NRTL
Certification		EMC	FCC Class "A" / CE
		ErP / Energy Star	X/0
		ePEAT (US only)	X
Ops Compatil	oility	OPS type compatible	X
	,	OPS Power built in	X
		SuperSign CMS	0
Software Compatibility		SuperSign Control / Control+	0/0
		SuperSign WB	0
		SuperSign Media Editor	0
		Promota	O (Not available for EU / CIS)
		LG ConnectedCare	0
Accessory		Basic	Remote Controller (include battery 2ea), Power Cord, QSG, HDMI Cable, Phone to RS232C Gende

del to model. Colour/shades may vary due to printing restrictions. E&OE As a continuing policy of product development at LG Electronics, the design and specifications are subject to change. They may vary fi GLG B2B CUSTOMER CARE



LG Se rvice India Mobile App Availabl Google Play To know more about LG, visit www.lg.com/in For B2B Solutions/Product enquires, please write to b2Ds.solutions@lge.com For B2B Service, please write to b2bsupport.india@lge.com

Image: Construct And State Construction and State Constructing State Construction and State Construction a



